



iCLASS® Read/Write Reader Part Numbers and Options

Card Reader Description	Base Part No.	Current Rev. No.*	Color Options	Hardware Options	Configuration Setting Options ¹	iCLASS Elite Key ²	MIFARE CSN ³ or FIPS201 ⁴ Wiegand Output Mode	Keypad Configuration Setting Options ⁵	Optional US Government (FIPS201) Format	Optional Custom ⁶
iCLASS RW100 Contactless Smart Card Reader/Writer: Read/Write Mullion Mount Wiegand and RS232 or RS485 or USB (RoHS Compliant)	6101	B	G = Gray K = Black	(All Terminal Strip) T= RS232 4= RS485 U= USB B= Uart to Uart	00 01 02 03 04 05 06 07	0 1	0 1 2 3 4 5 6	For Keypad readers only	(N/A)	-XXXX Y
							7 8 9 A C D F G H I J	For Keypad readers only	-G3.0	
iCLASS RW300 Contactless Smart Card Reader/Writer: Read/Write European and Asian Back Box Mount Wiegand and RS232 or RS485 or USB (RoHS Compliant)	6111	B	G = Gray K = Black	(All Terminal Strip) T= RS232 4= RS485 U= USB B= Uart to Uart	00 01 02 03 04 05 06 07	0 1	0 1 2 3 4 5 6	For Keypad readers only	(N/A)	-XXXX Y
							7 8 9 A C D F G H I J	For Keypad readers only	-G3.0	
iCLASS RW400 Contactless Smart Card Reader/Writer: Read/Write US, European and Asian Back Box Mount Wiegand and RS232 or RS485 or USB (RoHS Compliant)	6121	B	G = Gray K = Black	(All Terminal Strip) T= RS232 4= RS485 U= USB B= Uart to Uart	00 01 02 03 04 05 06 07	0 1	0 1 2 3 4 5 6	For Keypad readers only	(N/A)	-XXXX Y
							7 8 9 A C D F G H I J	For Keypad readers only	-G3.0	
iCLASS RWK400 Contactless Smart Card Reader/Writer: Read/Write, with Keypad US, European and Asian Back Box Mount Wiegand Output, and/or RS-232/485 Output (RoHS Compliant)	6131	B	G = Gray K = Black	T = Terminal Strip	00 01 02 03 04 05 06 07	0 1	0 1 2 3 4 5 6	00 09 10 11 14 19	(N/A)	-XXXX Y
							7 8 9 A C D F G H I J	22	-G3.0	
iCLASS RWKL550 Contactless Smart Card Reader/Writer: Read/Write, with LCD and Keypad US, European and Asian Back Box Mount Wiegand Output, and/or RS-232/485, and/or USB Output (RoHS Compliant)	6171	A	K = Black	T = Terminal Strip	00 01 02 03 04 05 06 07	0 1	0 1 2 3 4 5 6	00 09 10 11 14 19 22	Not available at this time	-XXXX Y

*Revision numbers and availability are subject to change without notice. Consult factory for availability.

¹ Configuration Setting Options are as follows (Factory or Field Configurable):

00 = Beep on, LED normally red, reader flashes green on tag read 03 = Beep off, LED normally off, reader flashes green on tag read 06 = Beep on, LED normally off, host must flash red and/or green
 01 = Beep off, LED normally red, reader flashes green on tag read 04 = Beep on, LED normally red, host must flash green 07 = Beep off, LED normally off, host must flash red and/or green
 02 = Beep on, LED normally off, reader flashes green on tag read 05 = Beep off, LED normally red, host must flash green

² iCLASS Elite Key options (Factory or Field Configurable): See Application Note Number 28 for additional information on Key Management.

0 = Standard (Reads all iCLASS cards with unique keys diversified from HID master key)
 1 = Custom, not valid with FIPS201 options (Reads only iCLASS cards with unique keys diversified from matching site specific master key; consult factory for availability)

³ MIFARE Card Serial Number (CSN) Wiegand Output Modes are as follows (Factory or Field Configurable): Refer to the "iCLASS Reader Wiegand Output Configuration Guide" for more details.

0 = 32 bit 1 = 32 bit reverse (Same as 6055A and 6055BXX0011) 2 = 26 bit 3 = 34 bit 4 = 40 bit 5 = 37 bit 6 = 56 bit

⁴ FIPS201 (USA Government Smart Card) Formats: (G2.0 = PIV I, G3.0 = PIV II compatible)

7 = 200 bit, 8 = 64 bit, MSB, 9 = 64 bit, LSB, A = 40 bit, MSB, C = 40 bit, LSB, D = 75 bit GSC, F = HMAC + 200 bit, G = HMAC + 40 bit MSB, H = HMAC + 64 bit MSB, I = 80 bit combined, J = 32 bit HMAC

For more information on the FIPS201 outputs, please refer to the output selection guide: http://www.hidcorp.com/pdfs/products/gsc_technote.pdf (For additional outputs, expiration date, GUID, TWIC please contact HID for a Command Card).

⁵ Keypad data is output via Wiegand cable. Reader processes keystrokes. Configuration Setting options:

00 = Buffer one key, no parity, 4 bit message 09 = Buffer one key, add compliment, 8 bit message (Dorado) 10 = Buffer six keys and add parity
 11 = Buffer one key and add parity 14 = Buffer one to five keys (Standard 26 bit output) 19 = Buffer four keys and add parity
 22 = Local PIN Verify. Requires User PIN code to be programmed into the iCLASS Credential at the factory or by using the iCLASS Card Programmer (please consult factory for availability.)

⁶ Contact Factory for pricing, availability, and minimum order quantity.

Readers that are RoHS compliant (RoHS = Restriction of the use of certain hazardous substances in electrical and electronic equipment) will be appropriately marked on reader and box.